



COST-EFFICIENT SINGLE RADIO 802.11A/B/G/N WIRELESS ACCESS POINT

AP 621

The AP 621 combines the power WiNG 5 intelligence at the edge with the cost-efficiency of a single radio thin wireless access point. When deployed with a wireless controller, the access point offers top 802.11a/b/g/n performance along with direct forwarding, security and QoS services at the edge.

UNIQUE VALUE

The AP 621 is a thin (dependent) multipurpose access point designed to lower the cost of deploying and operating a secure, reliable 802.11n wireless LAN (WLAN) in branch offices or headquarters facilities. The access point features a MIMO radio, superior receive and transmit sensitivity, and a GigE WAN uplink port. The AP 621 is easily managed remotely by a Motorola RFS 7000 or other wireless controller. The embedded WiNG 5 intelligence ensures that traffic is locally forwarded along the most efficient paths without sacrificing quality of service and security implemented at the access point itself.

AUTOMATIC CHANNEL AND POWER OPTIMIZATION

Common problems such as building attenuation, electronic interference or sub-optimal access point placement are minimized as the SMART RF feature of the switch/controller automatically optimizes power and channel selection so each user gets always-on high-quality access and mobility.

HIGH RELIABILITY

The AP 621 is designed to optimize network availability through its central and pre-emptive intelligence which dynamically senses weak or failing signals, securely moves mobile users to alternate APs, and boosts signal power to automatically fill RF holes and ensure uninterrupted mobile user access.

GAP-FREE SECURITY

Security includes layer 2-7 stateful packet filtering firewall, AAA RADIUS services, Wireless IPS-lite, VPN gateway, and location-based access control.

FAST AND EASY DEPLOYMENT

The access ports require no configuration or manual firmware maintenance. The Motorola wireless controller discovers access points on the network and automatically downloads all configuration parameters and firmware, greatly reducing installation, maintenance and troubleshooting costs for Layer 2 and Layer 3 deployments.

LESS IS MORE

Motorola's WiNG 5 WLAN solutions offer all the benefits of 11n—and then some. Our distributed architecture extends QoS, security and mobility services to the APs so you get better direct routing and network resilience. That means no bottleneck at the wireless controller, no latency issues for voice applications, and no jitter in your streaming video. And with our broad selection of access points and flexible network configurations, you get the network you need with less hardware to buy. Let us show you the less complicated, less expensive way to more capacity, more agility, and more satisfied users.

PRODUCT SPEC SHEET

AP 621

DEVICE AND NETWORK ACCELERATION

Device and network performance can be accelerated through a virtual LAN feature via the switch/controller. Each AP 621 access point can be virtualized into four unique VLANs which can be customized to direct

broadcast traffic to the intended recipient. This reduces overall network traffic while improving device performance and battery life up — to 25%. This also reduces the overall number of access points required to provide unique device services.

FEATURES

Full 802.11n performance with standard 802.3af

Simplifies and reduces total cost of installation using standard Power-over-Ethernet (PoE)

Multiband Operation

Supports both 2.4 Ghz and 5.0 Ghz frequency bands

Mobility

Supports fast secure roaming

Application Support

Supports Call Admission Control, for optimized VoWLAN performance, as well as video streaming and data throughput for 802.11 a/b/g/n clients

Load balancing, pre-emptive roaming and rate scaling

Increases reliability and resilience of the wireless network to support mission critical applications

AP 621 SPECIFICATIONS CHART

| PHYSICAL CHARACTERISTICS | AP 621 (INTERNAL ANTENNA) | AP 621 (EXTERNAL ANTENNA) |
|--|---|---|
| Dimensions: | 6.0 in. L x 5.5 in. W x 1.63 in. H 15.24 cm L x 13.97 cm W x 4.11 cm H | 6.0 in. L x 5.5 in. W x 1.63 in. H 15.24 cm L x 13.97 cm W x 4.11 cm H |
| Weight: | 0.60 lbs./0.272 kg | 0.60 lbs./0.272 kg |
| Part number: | AP-0621-60010-US AP-0621-60010-WR | AP-0621-60020-US AP-0621-60020-OUS AP-0621-60020-WR |
| Available mounting configurations: | Ceiling-mount (to suspended ceiling T-bars, below tile); wall mount | Ceiling-mount (above tile); wall-mount |
| Plenum rated: | Yes, certified to UL 2043 | |
| LED indicators: | 2 LED indicators with multiple modes indicating 2.4GHz/5 GHz Activity, Power, Adoption and Errors | |
| WIRELESS DATA COMMUNICATIONS AND NETWORKING | | |
| Data rates supported: | 802.11b/g: 1,2,5.5,11,6,9,12,18,24,36,48, and 54Mbps 802.11a: 6,9,12,18,24,36,48, and 54Mbps 802.11n: MCS 0-15 up to 300Mbps | |
| Network standard: | 802.11a, 802.11b, 802.11g, 802.11n | |
| Wireless medium: | Direct Sequence Spread Spectrum (DSSS) and Orthogonal Frequency Division Multiplexing (OFDM), and Spatial Multiplexing (MIMO) | |
| VLANs/WLANs supported: | VLANs and WLANs are controller-dependent | |
| Uplink: | Auto-sensing 10/100/1000Base-T Ethernet | |
| RADIO CHARACTERISTICS | | |
| Operating channels: | 5GHz: All channels from 5180 MHz to 5825 MHz 2.4GHz: 2412-2472 MHz Actual operating frequencies depend on national regulatory limits | |
| Maximum available transmit power: | 24dBm | |
| Transmit power Adjustment: | 1dB increments | |
| Antenna configuration: | 2x2 MIMO (transmit on two and receive on two antennas) | |
| Operating bands: | FCC EU 2.412 to 2.462 GHz 2.412 to 2.472 GHz 5.150 to 5.250 (UNII -1) 5.150 to 5.250 GHz 5.725 to 5.825 (UNII -3) 5.150 to 5.350 GHz 5.725 to 5.850 (ISM) 5.470 to 5.725 GHz | |

Continued on next page...

AP 621 SPECIFICATIONS CHART (continued)

| USER ENVIRONMENT | AP 621 (INTERNAL ANTENNA) | AP 621 (EXTERNAL ANTENNA) |
|--------------------------|-------------------------------------|---------------------------|
| Operating temperature: | 32°F to 104° F/0°C to 40° C | |
| Storage temperature: | -40°F to 158° F/-40°C to 70° C | |
| Operating humidity: | 5%-95% (non-condensing) | |
| Operating altitude: | 8,000 ft./2438 m | |
| Storage altitude: | 15,000 ft./4572 m | |
| Electrostatic discharge: | +/- 15 kV (Air), +/- 8 kV (contact) | |

POWER SPECIFICATIONS

| | |
|--|---|
| Operating voltage: | 802.3af supply: 48 VDC @ 12.95W (typical), 36 VDC to 57 VDC (range) |
| Operating current: | 270mA rms at 48V |
| Integrated Power-over-Ethernet support: | Standards-based IEEE 802.3af |
| Typical Operational RMS Power Consumption: | 10W (209mA at 48V) |

MAXIMUM RADIO TRANSMIT POWER:

| BAND | SINGLE ANTENNA COMPOSITE TRANSMIT POWER | DUAL ANTENNA COMPOSITE TRANSMIT POWER |
|---------|---|---------------------------------------|
| 2400MHZ | +24 dBm | +27 dBm |
| 5200MHZ | +20 dBm | +23 dBm |

ANTENNA PORT SPECIFICATON

| | | |
|-------|---|--|
| Type: | Integrated 2.4 GHz and 5.2 GHz Dual-Antenna Elements | Two RP-SMA connectors for external antennas (not included) |
| Band: | 2.4 GHz to 2.5 GHz; 5.180 GHz to 5.850 GHz (actual operating frequencies depend on regulatory rules and certification agency) | |

INTERNAL ANTENNA INFORMATION

| INTERNAL ANTENNA DESCRIPTION | VALUES |
|------------------------------|--------|
| Peak gain, 2.4GHz band | 3.0dBi |
| Peak gain, 5.2GHz band | 6.0dBi |

REGULATORY

| | |
|--------------------------------|--|
| Product safety certifications: | UL 60950, cUL, EU EN 60950, TUV and UL 2043 (external antenna) |
| Radio approvals: | FCC (USA), Industry Canada, CE (Europe) |

Continued on next page...

PRODUCT SPEC SHEET

AP 621

**CONDUCTED RECEIVER SENSITIVITY
(ANTENNA ELEMENT NOT INCLUDED)**

(typical) at antenna housing connector, 2400MHz band

| Rate/MCS | Mode | Sensitivity (dBm) |
|----------|--------|-------------------|
| 1 | Legacy | -95 |
| 2 | Legacy | -95 |
| 5.5 | Legacy | -95 |
| 11 | Legacy | -92 |
| 6 | Legacy | -96 |
| 9 | Legacy | -96 |
| 12 | Legacy | -95 |
| 18 | Legacy | -93 |
| 24 | Legacy | -89 |
| 36 | Legacy | -86 |
| 48 | Legacy | -82 |
| 54 | Legacy | -81 |
| MCS0 | HT20 | -96 |
| MCS1 | HT20 | -94 |
| MCS2 | HT20 | -91 |
| MCS3 | HT20 | -88 |
| MCS4 | HT20 | -85 |
| MCS5 | HT20 | -81 |
| MCS6 | HT20 | -79 |
| MCS7 | HT20 | -78 |
| MCS8 | HT20 | -93 |
| MCS9 | HT20 | -90 |
| MCS10 | HT20 | -87 |
| MCS11 | HT20 | -85 |
| MCS12 | HT20 | -82 |
| MCS13 | HT20 | -77 |
| MCS14 | HT20 | -76 |
| MCS15 | HT20 | -74 |
| MCS0 | HT40 | -92 |
| MCS1 | HT40 | -90 |
| MCS2 | HT40 | -88 |
| MCS3 | HT40 | -85 |
| MCS4 | HT40 | -82 |
| MCS5 | HT40 | -78 |
| MCS6 | HT40 | -76 |
| MCS7 | HT40 | -75 |
| MCS8 | HT40 | -89 |
| MCS9 | HT40 | -86 |
| MCS10 | HT40 | -84 |
| MCS11 | HT40 | -81 |
| MCS12 | HT40 | -78 |
| MCS13 | HT40 | -73 |
| MCS14 | HT40 | -72 |
| MCS15 | HT40 | -70 |

**CONDUCTED RECEIVER SENSITIVITY
(ANTENNA ELEMENT NOT INCLUDED)**

(typical) at antenna housing connector, 5200MHz band

| Rate/MCS | Mode | Sensitivity (dBm) |
|----------|--------|-------------------|
| 6 | Legacy | -94 |
| 9 | Legacy | -93 |
| 12 | Legacy | -93 |
| 18 | Legacy | -91 |
| 24 | Legacy | -87 |
| 36 | Legacy | -84 |
| 48 | Legacy | -80 |
| 54 | Legacy | -79 |
| MCS0 | HT20 | -94 |
| MCS1 | HT20 | -92 |
| MCS2 | HT20 | -90 |
| MCS3 | HT20 | -86 |
| MCS4 | HT20 | -84 |
| MCS5 | HT20 | -79 |
| MCS6 | HT20 | -78 |
| MCS7 | HT20 | -76 |
| MCS8 | HT20 | -91 |
| MCS9 | HT20 | -88 |
| MCS10 | HT20 | -86 |
| MCS11 | HT20 | -83 |
| MCS12 | HT20 | -80 |
| MCS13 | HT20 | -75 |
| MCS14 | HT20 | -74 |
| MCS15 | HT20 | -72 |
| MCS0 | HT40 | -90 |
| MCS1 | HT40 | -88 |
| MCS2 | HT40 | -86 |
| MCS3 | HT40 | -83 |
| MCS4 | HT40 | -80 |
| MCS5 | HT40 | -76 |
| MCS6 | HT40 | -74 |
| MCS7 | HT40 | -73 |
| MCS8 | HT40 | -88 |
| MCS9 | HT40 | -85 |
| MCS10 | HT40 | -82 |
| MCS11 | HT40 | -80 |
| MCS12 | HT40 | -76 |
| MCS13 | HT40 | -72 |
| MCS14 | HT40 | -71 |
| MCS15 | HT40 | -69 |

For more information on how the AP 621 can benefit your business, please visit us on the web at motorola.com/wlan or access our global contact directory at www.motorola.com/enterprisemobility/contactus



Part number: SS-AP621. Printed in USA 02/12. MOTOROLA, MOTO, MOTOROLA SOLUTIONS and the Stylized M Logo are trademarks or registered trademarks of Motorola Trademark Holdings, LLC and are used under license. All other trademarks are the property of their respective owners. ©2012 Motorola Solutions, Inc. All rights reserved. Specifications are subject to change without notice.

G3-29-112

